PocketBook Ultra



User Manual

Firmware 5.12

Table of Contents

SAFETY PRECAUTIONS	6
APPEARANCE	11
TECHNICAL SPECIFICATIONS	13
GETTING STARTED	14
Charging Battery	14
Device management	16
Main menu overview	17
Notification panel	18
Gestures	19
Working with On-Screen Keyboard	20
Frontlight	22
Connecting to the Internet	22
Inserting Micro SD Card	25

READING BOOKS	26
Gestures in Reading Mode	27
Reading Menu	28
Social networks & ReadRate	29
Contents	34
Bookmarks	35
Dictionary	36
Notes	37
Text-to-Speech (voice)	38
Reading settings	39
Text Format Books	39
PDF & DjVu	40
EPUB	41
Following Links	42
Loading Files	42
Library	48
PocketBook Cloud	52
APPLICATIONS	56
Book Store	57

ISBN-scanner	60
Standard Apps	62
Camera	62
Notes	64
Scribble	65
Calculator	65
Calendar & Clock	65
Gallery	66
Documents	67
Audio-player	70
Games	71
Klondike	71
Sudoku	71
Chess	72
Interactive Apps	72
RSS News	72
PocketBook Sync	75
Dropbox PocketBook	79
Send-to-PocketBook	81

SETTINGS	85
Wi-fi	85
Accounts and Synchronization	86
Personalize	91
Languages	94
Date/Time	95
Camera	95
Saving Battery	95
Maintenance	96
Software	99
About Device	100
FIRMWARE UPDATE	101
TROUBLESHOOTING	104
CUSTOMER SUPPORT	106
COMPLIANCE WITH INTERNATIONAL STANDARDS	107

Safety Precautions

Before start working with the Device, please, read this section carefully. Following these instructions will help you ensure your safety and extend service life of the Device.

Storage, Carriage and Usage Conditions

Device operating temperature range is 0°C to 40°C, so don't expose the Device to excessively high or low temperatures. Never leave cables near heat sources. Heated cables or their insulation may become deformed or damaged, which could lead to fire or electric shock.

Try to avoid next impacts:

Electrostatic Excessive mechanicharaes

cal pressure

Strong electromaanetic fields

Direct sunlight UV electromaanetic radiation

Liquids or damn

Direct flame or smoke













Maintenance

- Do not leave the Device for a long time in poorly venti- lated environment, e.g. in a car or in closed tight boxes/ packaging.
- ⊗ Neither drop nor try to bend the Device.
- ②Protect the screen from objects that may scratch or damage it. To ensure adequate protection of the screen, we recommend storing the Device in a protective and/or hard cover.
- ⊗ Do not disassemble or modify the book reader.
- ⊗ Do not use the Device with a damaged battery or charger (broken case, poor contact, broken feed cable). If the battery is damaged (cracked case, leakage of electrolyte, off-shape etc.) it should be replaced by the authorized personnel. Usage of home-made

or modified batteries may cause an explosion and/or damage the Device.

⊗ Do not use organic or inorganic solvents (e.g. benzoyl etc.) to clean the screen/case.

Use a soft cloth to remove dust from the Device's surface. Apply a few drops of distilled water to remove dirt.

Up to five faulty pixels are acceptable in the screen and do not constitute a warrantable defect of the screen.

If the device has not been used for a long time, the battery charge indicator may not work when the charger is connected. In this case, connect the charger, let the device charge for 1 hour, then disconnect and reconnect the charging device or USB cable. The device can then be used as normal.



To prevent possible hearing damage, do not listen at high volume levels for long periods.

By the end of product guarantee term, please contact the nearest authorized service facility for examination on the subject of security is maintained.

For detailed information about service centres in your region please visit the official website of PocketBook International: http://www.pocketbook-int.com.

RF Safety

The Device receives and transmits radio frequencies and may interfere with radio communications and other electronic equipment. If you use personal medical Devices (e.g. a pacemaker or hearing aid) please contact your doctor or the manufacturer to learn whether or not such medical devices are protected against external RF signals.

Do not use wireless communication in places where it is prohibited, e.g. onboard a plane and in hospitals — this may affect airborne avionics or medical equipment.

Utilization



Incorrect disposal of this Device may have adverse impacts on the environment and public health. To prevent such consequences follow the device-specific disposal requirements. Recycling of these materials helps pre-

serve natural resources. For more information regarding recycling issues please contact local municipal authorities, your domestic waste collection service, store where you purchased the Device, or the authorized service centre.

Disposal of electric and electronic components (the Directive is applicable to the EU and other European countries where separate waste disposal systems exist). In other countries dispose batteries accordingly to local laws.

Do not destroy the battery by burning it to avoid the danger of explosion

Appearance




- 5. **Side right button** turns page forward;
- 6. Camera 5 MP camera with autofocus:
- 7. LED flash:
- 8. Protective cap;
- Side left button turns page forward;

- 1. Home return to Main menu;
- 2. **Backward** in reading mode turns page backward; in navigation mode goes to the previous menu or page of the list;
- 3. Forward turns page forward;
- 4. **Menu** open context menu (if available). Continuous press switches the frontlight on/off (See *Frontlight* section of the manual);



Appearance 12



- 10. Hand-strap hole;
- 11. 3.5 mm audio jack;
- Micro-USB socket connect the Device to a PC or a charger using USB-cable;
- 13. microSD slot to install external microSD/SDHC card (up to 32 GB);
- 14. On/Off (power button) continuous press turns the Device on/off.

NOTE You can configure key mapping to your own in *Settings > Personalize > Key mapping*. Navigation and page turning buttons mapping depends on screen orientation.

Technical Specifications

Display 6" E Ink Carta capacitive multi-sensor 1024×758 display, 212 dpi, B&W

Frontlight Yes

CPU Freescale i.MX6 Solo Light

RAM 512MB (DDR3)

Storage 4 GB *

Operating system Kernel Linux 3.0.35

Communications Micro-USB

Wi-Fi (b/g/n)

Battery Li-Pol, 1500 mAh **

Memory slot microSD/SDHC up to 32 GB

Audio output 3.5 mm earphones jack

PDF, EPUB (including DRM-protected);

Book formats

DJVU, FB2, FB2.ZIP, DOC, DOCX, RTF,
PRC, TCR, TXT, CHM, HTM, HTML, MOBI,
ACSM

Image formats JPEG, BMP, PNG, TIFF

Audio format MP3

Camera 5MP with autofocus and flash

Dimensions 162,7×106,7×7,9 mm

Weight 175 g

^{*} The actual available internal storage size may vary depending on the software configuration of your device.

^{**} Battery life and values mentioned above might vary depending on usage mode, connectivity and settings.

In this chapter you will learn how to prepare the Device to work and about its main control features.

CHARGING BATTERY

To extend battery lifetime, it's recommended to charge the Device for the first time from 8 to 12 hours.

You can charge the battery from (1) PC using USB-cable or from (2) the power line using a charger (optional).



To charge the battery for the first time, do the following:

- Connect the Device to a computer or charger with USB-cable. The device will turn on as soon as charging starts.
- When the battery is fully charged, you can disconnect the cable from the Device which is ready for usage.

If the Device is on when you connect the cable to PC, a dialog window asking to select action – *PC link* or *Charge* – will appear. Charging starts only if the appropriate mode was selected

DEVICE MANAGEMENT

Turn on	Press On/Off button. When the Device is ready to operate, Main menu or last opened book will appear, depending on settings.		
Turn off	Press and hold On/Off button for about two seconds until the Device goes off.		
Lock	You can lock your Device in three ways: 1. Press On/Off button. 2. Invoke Task Manager. Touch icon 1 to block your Device. 3. You can set automatic key lock or power off: go to Settings > Saving Power > Power off after or Lock device after, and set the idle time before power off or locking Device.		
Unlock	Press On/Off button.		
Restart	In case if your Device 'freezes' (don't respond to keys presses or screen touches, you must give the device time (up to 30 seconds) to process commands. If it does not help, you can restart it by pressing On/Off button for 10 seconds.		
Task Manager	You can invoke Task Manager in two ways: • by touching at the notification bar icon; • by continuous press on the Home button. Task Manager gives quick access to some Device control features: • close running applications: press X against an application in the list. • If Lock Device. To unlock, press On/Off button. • Open wireless connections list. • Take a screenshot. • Turn off the Device.		

MAIN MENU OVERVIEW



Notification panel

Touch or slide down the icon _____ to open a *Notifica-*tion panel.

NOTE: You can open Notification panel also pressing a Menu button.

Notification panel gives an easy access to configuration of <u>Wi-Fi</u> and <u>Frontlight</u>, <u>Sync</u> of network services, <u>Task manager</u>, device <u>Settings</u> and <u>Search</u>.

Also the news on ReadRate are displayed on it.

NOTE: To see the ReadRate news, please, authorize to the service first. Go *Settings > Accounts and Synchronization > ReadRate* and *Log in* the service.

GESTURES

CAUTION! Touch screen of the Device is sensitive enough and is a fragile detail. To avoid its damage, please, touch it carefully while controlling the Device with gestures.

Tap

Opens an element (book, file, folder application or menu item).



Touch & hold

Opens context menu of an element (if available).



Slide

Turns pages of a book or a list; moves an image: slide your finger across the screen.



Flick

Scrolls lists: move your finger across the screen rapidly.



Scaling

Changes the image scale: place two fingers on a screen and pinch them together to zoom out or spread them apart to zoom in.




WORKING WITH ON-SCREEN KEYBOARD

On-screen keyboard is used when it's necessary to enter text information, for example, for search or network connection credentials.

To type a symbol, press a key.

To switch to another input language, press the current language button. To add the language to the on-screen

keyboard layout go to Settings > Languages > Keyboard Layouts.



- 1. Change case;
- 2. Enter the typed text;
- 3. Close the on-screen keyboard;
- 4. Erase last typed symbol;
- 5. Change input language.

As you type a password (e.g. Wi-Fi credentials) icon will appear on a text field. Touch it to see typed symbols.

FRONTLIGHT

To turn on/off the frontlight, press and hold the Menu button for 1 second.

Also you can adjust the frontlight level using the slider in the notification bar.



CONNECTING TO THE INTERNET

The Device can be connected to the Internet using Wi-Fi networks. When you open an application that requires an Internet connection (eg, *Browser* or *BookStore*) Wi-Fi connection is established automatically. If a known network is not available, the list of available wireless connections opens. If the network to which you want to connect is secured, enter the network password using the onscreen keyboard.

Also, Wi-Fi connection can be *enabled/disabled* by clicking the icon on the notification panel. If a known network is available, the connection is established automatically, otherwise - opens a list of available networks.

Advanced Settings

If it is needed to configure network settings manually select *Settings > Wi-Fi*, go to the selected network and click *More...* at the bottom of the screen:


- You can change IP address configuration:
 - DHCP get IP address automatically (if DHCP server is configured);
 - Manual (for skilled users) enter networks parameters manually from the on-screen keyboard.
- If the network you need to connect to has a proxy server, you can specify its parameters in *Proxy configura*tion section.

Connection to a hidden network

- 1. Select Settings > Wi-Fi
- **2.** Open *Connection to a hidden network* and enter its SSID from the on-screen keyboard in the *Network name* (SSID) field.
 - 3. Select security type in the corresponding list:
 - None for an open network;
 - Simple (WEP) after you select this option, you will need to specify WEP Authentication type Open System or Shared Key either.
 - WPA/WPA2 PSK you will need to enter network key (up to 64 symbols).
- **4.** To check network configuration and connect to a network, return to the *Connection to hidden network* section and press *Connect*.

INSERTING MICRO SD CARD

The Device already has 4 GB of internal storage, but you can extend it by using micro SD card (up to 32 GB). Insert it to the slot, like it is shown on a figure, and slightly push until card will be fixed.



To eject the card, slightly press on its edge until it will be unfixed, and pull it to get.

ATTENTION! If your SD card get stuck, do not try to eject it by yourself and immediately call Customer Support.


Reading Books

In this chapter you will learn how to read e-books and configure reader software for the most comfortable reading. The Device supports next book formats: PDF, EPUB (including Adobe DRM-protected); FB2, FB2.ZIP, DOC, DOCX, TXT, DjVU, RTF, HTML, HTM, CHM, TCR, PRC, MOBI, ACSM.

To open a book, touch its icon on *Recent Books* or *Library* section. If you opened a book before, it will be opened at the page you've finished reading. In some book formats (e.g. fb2 or ePub) after opening a book reader application will count pages – this is indicated with '...' sign instead of a page count in a status bar. During page calculation some features will not be available.

To bring up reading menu, touch the center of the screen or press **Menu** button.

GESTURES IN READING MODE



- X Close book;
- ☐ Make a bookmark;
- Turn pages forward;
- Turn pages backward;

Pressing in the center of the screen evokes the Reading menu

Page turning






Scaling







23/102

Pull the slider to turn pages or touch the page number to input the digits of needed page

SOCIAL NETWORKS & READRATE

margins will be crd

Now you will be able to take advantages of social networks on your Pocketbook: share quotations from books, add comments, tell what you are reading or have read, like or don't like. ReadRate also allows you watching the friends' events and obtaining information about the most popular books.

s mode text is formatted to display een. Reflow mode is supported for tables and pictures cannot tode; ling page to the screen width; ling — allows to decrease mar insteade section of the reading many gins cropping menu:

You need an Internet connection to send events to social networks. To open the ReadRate menu, touch the cicon in the reading menu.

Reading status and Book Rate

- **1.** Touch one of the options (*Now reading*, *Have read*, *Plan to read*, *Recommend* or *Rate* with stars from 1 to 5).
- Enter data (E-mail and password) of one of your accounts: in social networks or in the market Book Store.



3. In consequence there will be created the ReadRate profile, you can link another social networks accounts to it. After authorization the window appears:



4. Select social networks, where you want to send news: *Facebook, Vkontakte, Odnoklassniki, Twitter* – icons of chosen networks will become hefted.



- If the chosen social network wasn't linked to the ReadRate profile, you will be proposed to link them.
 - 6. Confirm your choice by pressing OK.

All actions are displayed by default in your ReadRate profile and in the news line of chosen social networks.

After activating *Now reading, Have read* or *Plan to read* statuses, their icons become colored — ■, ✓ and •.

Recommend

- 1. Touch Recommend option.
- After that the scenario Reading status and Book Rate is performed, beginning from 2 item.



- Choose a friend from a list or enter user email to send a recommendation to him/her.
- **4.** Enter a comment and confirm sending by pressing *Recommend*.

Share quotation

To share quotation from a book:

- After continuous touch on the screen in the opened book, creeper of text selection appear.
 - **2.** Select quotation and press *Share* icon 🗓 .
- After that the scenario Reading status and Book Rate is performed, beginning from 2 item.



4. All actions of your friends on ReadRate are displayed in Notification panel of your Device:

Book recommendations from ReadRate

+37 events of friends on ReadRate

5. You can *Delete* or *Open* event. When you open it all new friends' actions on ReadRate will be displayed.

ReadRate news / February 12, 2014

** Ruslan Pogutsa rated the book ** A Christmas Carol" (Charles Dickens)

<u>Ruslan Pogutsa</u> rated the book " <u>Benutzerhandbuch PocketBook"</u>

To delete your social networks accounts information for ReadRate, go to Settings > Accounts and Synchronization > ReadRate > Remove ReadRate authorization on your PocketBook.

If you want turn off temporarily the ReadRate functionality, set *Off* in *Settings > Accounts and Synchronization > Read-Rate > ReadRate Status*. After this operation all ReadRate options becomes hidden and inactive.

ECONTENTS

If a book has table of contents, you can open it by selecting the corresponding reading menu item.

Content section contains three insets:

- Sections (book's chapters names);
- · Bookmarks (made during reading);
- Notes (graphic or text).

If table of contents has more then one level, higher level entry will be marked with '+' sign – touch it to expand. '+' sign will be changed to '-' – touch it to collapse.

To open contents menu touch and hold your finger on the screen or press key. Using the menu you can open contents entry, edit or delete notes and bookmarks.

In addition, you can expand or collapse all the table of contents entries

BOOKMARKS


To create a bookmark, touch right top corner of the screen. A dog ear mark will appear. To delete a bookmark, touch this mark again and confirm deletion.

Also you can add/remove bookmarks by selecting the corresponding reading menu item. All the bookmarks are displayed in book contents.

<	Contents / User Manual PocketBook		
	≡	П	
	Bookmark		18
	Bookmark		46
	Bookmark		65




Touch and hold a word to open a panel allowing you to search for translation using one of installed dictionaries or find a word in Google. Also after selecting Dictionary item, a window with dictionary entry of a selected word appears. Next tools are available:





Notes allows you to save favorite book fragments and make handwritten records directly in the text. All the notes will be displayed in book's table of contents. To enter notes mode, select ② *Note* reading menu section.



NOTE Handwritten notes are not available for DjVu books.


After you will enter Notes, a tooltip window will appear.

All notes are visible from section Notes at Application panel.



Text-to-Speech (TTS) software is designed to transform text into speech.

To start TTS, open reading menu and select *Voice*. TTS control panel will appear:



Progress bar indicates a fragment read currently, pages are turned automatically as you listen.

Initially there are 3 TTS packages are installed on the Device.



You can customize the display of books depending on your preferences.

Text Format Books

In text format books (TXT, FB2, DOC etc.) there are options to configure reader software: font, font size, line spacing, page margins width, hyphenations (*on/off*), encoding.



NOTE: You can change font size using the scaling gesture: pinch two fingers together to reduce font size and spread fingers apart to enlarge.

PDF & DjVu

You can change only the whole page scale only (except *Reflow* mode for PDF).

Pinch two fingers together to zoom out or spread them apart to zoom in or slide a finger upwards the right side of screen to zoom in or downwards – to zoom out, respectively.



Under *Mode* reading menu section you can zoom pages or select viewing mode:

- 1. Fit width scaling page to the screen width;
- 2. Whole page one page scaling;

- **3.** Columns for reading books with columns. To navigate the page use navigation buttons. A page will be turned after bottom edge of the sheet reached;
- **4.** Reflow in this mode text is formatted to display completely on the screen. Reflow mode is supported for PDF books only. Some tables and pictures cannot be displayed in the Reflow mode:
- **5.** Margins cropping allows to decrease margins width or heigth. In *Mode* section of the reading menu, press \sim to extend *Margins cropping* menu:
 - off turn off margins cropping;
 - automatic margins will be cropped automatically
- manual move arrow buttons to set margins width and heigth of margins.

EPUB

In books in EPUB format there are options to configure reader software: font, font size,line spacing, page margins width

FOLLOWING LINKS

To follow a footnote, internal or external link, touch to enter links mode. To exit this mode, touch top left corner of the screen.

If a link follows to a web-site, it will be opened with Device built-in browser. To return to reading, press *Exit* in Browser menu.

LOADING FILES

Connect the Device to the PC using microUSB cable.

NOTE The Device should be kept on while transferring files.

You will be prompted to select USB mode: *PC Link* or *Charge* either. Select *PC Link*. Operating system of computer will detect Device's storage as removable disk (if SD

card installed – as two ones). Now you can copy files to the Device or SD card using Explorer or other file manager.

ATTENTION! After copying files safely remove the Device before disconnect the cable!

Downloading protected e-books (Adobe DRM)

Registration at <u>www.adobe.com</u> is required to use e-books in protected format (*Sign in > Create an Adobe Account*).

Download via *.acsm

1. Visit www.adobe.com via your browser;

NOTE: the current version of your browser on the Device does not support Flash Player

- 2. Open Menu > Products > All products;
- **3.** Follow the link *Digital Editions* in the alphabetical index of products.

- Open Visit the sample eBook library at the bottom of the page to enter the library;
 - 5. Choose a book and click Download item.
- **6.** A download window will appear on the screen. The file name should contain the name of the book and the file extension .acsm. Click Save.
- **7.** After the file is saved on your PC, a link as URLLink. acsm will appear.

NOTE: The same sequence of actions allows downloading a link to a protected book from any online bookstore.

Do the following to open a protected (DRM) book on the Device:

- **1.** Copy the file of the link to a book (*.acsm) to your Device.
 - 2. Find and open the file on your Device.
- **3.** Follow the on-screen instructions to activate your Device. To do this, use the on-screen keyboard to enter the login and password of your account on www.adobe.com

into the *Device Activation* form. Then you will be able to download the book.

4. Download the book. After the download is complete, a full version of the book will be available for reading in the *Digital Edition* folder.

The downloaded book is protected (DRM) and cannot be opened by a non-registered user.

Download books via PC

1. Open the Adobe Digital Editions application.

NOTE: When connecting your Device to PC for the first time, *Adobe Digital Editions* prompts you to activate the new device. Use your registration data at www.adobe.com for this. If the Device is not activated, it will be impossible to copy a book from PC to device using *Adobe Digital Editions*. If you have previously used registration data in a firmware version earlier than 2.0.4 in the device for opening protected books then, when upgrading the software version, you will have to enter registration data at www.adobe.com for this. If the Device is not activated in a firmware version earlier than 2.0.4 in the device for opening protected books then, when upgrading the software version, you will have to enter registration data at www.adobe.com for this. If the Device is not activated, it will be impossible to copy a book from PC to device using Adobe Digital Editions. If you have previously used registration data in a firmware version earlier than 2.0.4 in the device were only the control of the control of

<u>com</u> once more to open such books again. Authorization of *Adobe*Digital Edition can be deleted in section Settings > Service > Delete

ADE authorization.

- 2. Select the Go to library view icon.
- 3. Click All items.
- 4. Choose a book and copy it to your Device.

Sync your device with network services

You can also upload files to the Device synchronizing device memory with personal accounts of network services - PocketBook Sync, Send-to-PocketBook, PocketBook Cloud and Dropbox.

Variant 1

- Open Settings > Accounts and Synchronization;
- Select the appropriate network service (Pocket-Book Sync, Send-to-PocketBook, PocketBook Cloud or Dropbox);

Select the synchronization option.

Variant 2

- · Open Library;
- Call up the context menu of a folder of the service which you want to synchronize with your device;
 - Select the synchronization option.

For detailed information about work with network services see sections <u>PocketBook Sync</u>, <u>Send-to-PocketBook</u>, <u>PocketBook Cloud</u> and <u>Dropbox PocketBook</u>. Read more about configuring network services at the section <u>Accounts and Synchronization</u>.

Synchronization status can be viewed on the *Notification* panel.



During uploading or downloading files an animated icon \mathfrak{S} displays at the status bar. Touch the icon to open a window with the synchronization status of all services.

The icon in the status bar changes to ! if the error occurred during synchronization of one of the services. If all synchronization processes are completed without errors, the icon in the status bar disappears.

LIBRARY

Library is e-books file manager. Library menu allows to filter, group, sort, change appearance of the section and perform search.



1. Grouping criteria

Depending on selected criterion books are grouping by:

- · All Books;
- Authors;
- · Genres;
- Collections create your own shelves with books depending on your interests and preferences;
 - Favorites;
 - · Folders;
 - Formats;
 - · Series;
 - PocketBook Cloud.




The results of grouping can be be dispalyd as ascending (A-Z) or descending (Z-A).

2. Sorting criteria

- By opening date;
- · By addition date;
- By title;

By author.



3. Books list views

- Simple in this mode the cover icon of the book is displayed.
- **Detailed** in this mode there's added author, titele, thumbnails, information about file format and size, read percentage.

Context menu...

- ...opened by continuous touch...
- ...and allows proceeding with next file and folder operations:
 - · Book Info brief information about book/folder;
 - · Add to Collection;

- · Add to Favorites;
- File file operations:
 - Copy;
 - Move;
 - Delete;
- Upload to PB Cloud/ Remove from PB Cloud;
- Select multiple choice of files.

PocketBook Cloud

You can read your books on different devices and be sure that all your books, favorite attribute, collections and reading progress will be saved. You can have access to your books from any device on which you are logged in to the *PocketBook Cloud* account.

NOTE: PocketBook Cloud supports storing files in next formats: PDF (PDF, EPUB (including DRM-protected); TXT, FB2, FB2. zip, RTF, HTML, HTM, CHM, DJVU, DOC, DOCX, TCR, PRC, MOBI, ACSM). But synchronization of reading position is supported for now only in PDF and EPUB formats.

How to sign in

You can sing in to *PocketBook Cloud* service through a website, PocketBook Reader mobile application (for Android and IOS) or from your PocketBook e-ink reader.

During initial setup of your Device you will be suggested to sign in to *PocketBook Cloud* account or registration will be performed automatically if possible.

If you have skipped this step, the suggestion to sign in to PocketBook Cloud account will appear at the notification

panel.



To sign in:

1. Tap on this notification or go to the *Settings > Accounts and Synchronization > PocketBook Cloud*.

- You will be redirected to the login form, where you can sign in using your bookstore account or you can tap on <u>Don't have an account? Create!</u> link.
- **2.** A list of partners bookstores will be opened in Browser app. To continue, please, choose one of the suggested bookstores by clicking on its name.
- **3.** You will be redirected to the partner's bookstore website. Go to the *Sign in* form and create a new account according to the instructions.
- **4.** After that, please, return to *Settings > Accounts* and *Synchronization > PocketBook Cloud*, and type your account credentials you used to create a partner's bookstore account and press *Login* button.

Sync process

The auto synchronization of books list and reading position takes place at the time of:

- · login to the PocketBook Cloud account,
- · book opening,
- hook closure

book fold.

To enforce synchronization click on the sync icon \mathcal{Z} on the notification panel.

If there is no Internet connection on your Device you will have access only to the books, which are already on your Device. After the Internet connection is restored, all books will be synchronized.

If an error occurred during synchronization, please, check your Internet connection. If an Internet connection is established correctly try to sync your books lately.

File operations

 File storage. A dotted line of the frame around the book on PocketBook e-ink reader a means that the book is not loaded yet to the device memory and is stored only in your PocketBook Cloud account.

In this chapter you will learn about applications wich are preinstalled on your Device.

There is three apps which is brought out to the main menu:

- Library;
- BookStore;
- · Scanner.

The rest of the apps are available at the application bar. To invoke it touch the icon — at the main menu.





Library is e-books file manager, which allows to group, sort, change appearance of the section and perform search. Read more about this app at *Library*.




Book Store application provides quick and convenient licensed content download from Book Store portal (http://www.bookland.com/) to your Device. The internet connection must be active.

If you are already registered at the portal http://www.bookland.com/, press *I already have an account BookLand* and check if the login and password are entered correctly at Book Store settings.

Enter your account data at Book Store in the section *Settings > Accounts and Synchronization* in your Device.

If the connection with an account is set properly, you get access to all the features of a portal.

Press the *Personal Room* to expand options for work with a personal account:



 Top up the balance – top up the balance on a site BookLand or directly on the Device using the bank card (Visa, MasterCard, Maestro);

- Purchase history the list of goods, purchased at the store;
 - My cards used bank cards;
 - Exit.


Select the book and press *Buy* to purchase goods. Choose the format of a downloading book and press *Buy* and download on the page *Your* purchase. The bought file is moved to the folder *Library* > *Downloads* and is displayed on the wall of *Last* events of the Main Menu.

NOTE If there is no money on your balance, it will be offered to you to top up the balance on a site BookLand or directly on the Device using the bank card (Visa, MasterCard, Maestro).



ISBN-scanner — is an application for barcodes and QR-Codes decryption that allows retrieving quickly the encrypted information from them, such as text, web links or ISBN (International Standard Book Number).


To decrypt code point camera to QR- or barcode and place code in the middle of the rectangle on the screen, the Device will automatically identify it.



After decryption the application prompts to look for the found results on the Internet.

To view the *Scanning history*, click on the icon \blacksquare in the upper right corner of the screen.

To manage the elements of the list in the *Scanning History* call the context menu that opens by continuous touch.




STANDARD APPS



Camera

The Device has a 5 megapixel camera with autofocus and LED flash. With camera you can take pictures and scan barcodes and documents to create your own books.



To make pictures:

- 1. Go to Camera app.
- 2. Point the camera at the subject of photographing and click on the icon O at bottom of the screen or press Forward button.

NOTE: To set the flash (off /on) click on the icon \checkmark in the lower right corner of the screen.

3. Pictures can be seen in the app *Gallery*.

To scan documents:

- 1. Go to Camera app.
- **2.** Click on the icon at the top of the screen and the *Documents* section will open.
- **3.** Point the camera on the object of scanning and click on the icon O at the bottom of the screen or press **Forward** button.

4. After the photo is taken, the Device will offer to create document. To do that, press **OK** at the upper right corner of the screen.

To add photos to the document use button Add photo at the bottom of the screen.

Scanned document can be viewed and edited with application *Documents*. Details of the work with scanned materials read at section *Documents*.



In this section you can view all the notes made during reading. After you select a note, the table of contents of the book, where it was made, will open. Please, read more about notes creation and editing in *Notes*.



Calculator

Engineering calculator supports a wide range of mathematical operations, such as different numeric systems, trigonometric, logarithm, power and logical operations.



Calendar & Clock

Opens current month calendar and clock. Navigation ♠/▼ allows turning over a calendar. The button ● returns you to the current month. Read about date and time setting in <u>"Date/Time"</u> manual's chapter.



Scribble

Application for drawing. To select the drawing tool, use the application control panel:

Text: select the position and size of the text box. Text is entered with the on-screen keyboard;

A^I Font: change font and its size;

Pencil: a tool for drawing thin lines;

→ Marker: a tool for drawing thick lines;

Eraser: a tool for removing lines and text;

Back: cancel the last operation;

◆ 1/1 ► Current drawing/total number of drawings: change the current drawing;

New: start new drawing;

Delete drawing;

Exit application.

To save a picture, touch \Box icon. The current picture will be saved to the *My Pictures* folder in the root folder of the Device.

Gallery


Opens Library in the mode of viewing images (downloaded to the folder *Gallery*). The opened photo is displayed in a full-screen mode. To set a photo as *Power-off Logo*, to *Rotate* or view *Information* about it, touch the full-screen image to switch to the editing mode and press menu sign \equiv in the right

top corner of the screen. In the editing mode you can zoom a photo by zooming gestures and set the selected area as a logo.



Documents


Documents - an electronic file manager that allows you not only to view scanned documents, but also edit them, recognize the text on images and make your own books, converting images to PDF or TXT formats.



To edit images:

- 1. Open a document.
- 2. Select an image to edit and open with tap on it.

3. Click on the icon at the bottom of the screen to call up *Settings* panel.



NOTE: You can also call up image settings with the help of the context menu. Open context menu by long tap on the picture on the list of document and select *Edit*.

- **4.** To apply the selected settings click on the button
 ✓ in the upper right corner.
- **5.** To see the preview of recognized text click on the icon **.**

To recognize text:


- 1. Open a document.
- 2. Select an image and open it with tap on it.
- **3.** Click *Recognize Text* at the bottom of the screen.
- **4.** Select between options *Recognize all images* or *Recognize only this picture*.
 - 5. Choose the language of text recognition.

Once the process of text recognition is completed, you will be prompted to export the new document into PDF or TXT formats.

New created books can be viewed at the *Library* section.



Music player for playing .mp3 media files.



In the *Application menu* you can add audio files and folders with audio to the playlist, rearrange tracks, and save or clear playlist.





By means of the *context menu*, opened with a long press on the track, you can perform the following operations: view info about track, add to queue, or remove the file from the list.

GAMES



Klondike

Classic solitaire.



Sudoku

Popular Japanese puzzle. Press on an empty cell to select it. After that you can input in the selected cell the digit

you think should be in the cell or set labels — digits that you suggest may be in the cell. Digits and labels should be chosen from the bottom selection panel.



You can play versus your friend or the Device. If you are playing against the Device, you can select 10 difficulty levels.

INTERACTIVE APPS



RSS News

Application for adding and reading RSS feeds. To add RSS news feeds, open RSS setup. Select the Add RSS feed option. Enter the feed address using the on-screen keyboard.

To delete the feed, select it, open the context menu and select *Delete* command or press the *Recycle bin* icon $\widehat{\mathbf{u}}$.

To edit the feed, select it, open the context menu and select *Edit name* or *Edit URL* command. Edit the RSS feed name or address using the on-screen keyboard.

To update feed, select *Update* in the application menu. Updated content is added to the file with .hrss extension, and the file will be accessible for reading after updating. The news downloading status is displayed while updating. After the update file is available for reading off-line using the browser.

To read latest feeds, select *Read the latest news* option in the application's menu. The latest downloaded RSS feed updates open in browser.

News Archive: by selecting this option you can choose to read the previously stored updating RSS feeds.



Browser

This is an application for viewing web-pages. As you start Browser, you are suggested to connect to one of available wireless networks.

To enter website address, touch address bar, type an address from on-screen keyboard appeared and press *Enter*. To follow a link, just touch it. If a web-page doesn't fit a screen, you can scroll it: place your finger on the screen and move a page. Also, you can change scale of a web-page using zooming gestures (pinch or spread two fingers). Hardware buttons \triangle/∇ are used to scroll page vertically: ∇ scrolls down and \triangle scrolls up, respectively.

From browser menu you can view history of visited websites, downloads, favorites, adjust scale of displaying webpages, rotate a screen and configure the browser from *Settings* section. Under *Settings* you can clear history and cookies, disable/enable JavaScript and loading images.



To exit Browser, touch the corresponding item in browser menu



PocketBook Sync

PocketBook Sync service allows you to download all books, chosen on the book store, directly to your Device (or even to several devices).

PocketBook Sync is convenient because you can choose files from the store in advance and then download them on your Device in any time convenient for you.

Usage

NOTE: For correct work of PocketBook Sync time and date on the Device should be adjusted properly (*Settings* > *Date/time*).

To use *PocketBook Sync* you need to perform several simple steps:

Registration

- **1.** Register at the portal Book Store. (For example, at the portal www.bookland.com you need to add your Device to your account by entering a serial nuvber of the Device on the site).
 - 2. Authorize in PocketBook Sync. Do the following:
- launch the PocketBook Sync application and choose Authorize, or choose Login item in PocketBook

Sync Settings (Settings > Accounts and Synchronization > PocketBook Sync). If Wi-Fi connection has not been activated, the Device will generate a connection request).

 choose the store, where you are registered, from the list of content providers, and enter your account data.

Choosing and Sending Content to Your Device

Choose the books on the Book Store and send them to the Device. (For example, in the Book Store www.bookland.com you need to choose content in the tems section and press Send to PocketBook).

Downloading Content on the Device

Turn on Wi-Fi connection on your Device or choose *Up-date* in PocketBook Sync application (if Wi-Fi connection has not been activated, the Device will generate the connection request).

If Automatic connection is chosen in PocketBook Sync settings, Wi-Fi will be activated

automatically every half an hour for checking new links (if the Device is not powered off/not in sleeping mode). The list of downloads will be automatically loaded to the queue after successful setting connection.

If Automatic download is chosen in PocketBook Sync settings, the download will start automatically. If By request is chosen in PocketBook Sync settings, then a list of titles prepared for download to the Device will be displayed in the In queue section. You need to select one, several or all items in the list and choose Download (you can also delete undesirable links by choosing Delete).

You will see downloading and downloaded files in the *Downloads* section. Downloaded files are moved to the *Download folder*, location of which is defined in the PocketBook Sync settings (*Downloads* folder by default). The downloaded file is displayed on the wall of Last events of the Main Menu



Dropbox PocketBook

DropBox application allows to download files, added to Dropbox from any computer or any Device with installed Dropbox app or from the <u>Dropbox website</u>, to your Device. And you do not need to install anything to your Pocket-Book, it is enough to authorize in the service.

How to start using

- 1. Register in the Dropbox service (<u>www.dropbox.com</u>);
- **2.** Input your Dropbox account data (email address and password) on your PocketBook Device in the section *Settings > Accounts and Synchronization > Dropbox > Log-in* to authorize Dropbox. (The Wi-Fi connection should be on, otherwise you will be asked to turn it on);
- **3.** After successful authorization, the *Dropbox PocketBook* sync folder will be created in the Library of the Device. The *Application > Dropbox PocketBook* directory will show up in your Dropbox account, and after synchronization it will be available from other devices with Dropbox.

NOTE The application on your device will have access only to files in the *Application > Dropbox PocketBook* folder on the server

How to synchronize

Automatically:

- **1.** Files, added to the directory *Application > Drop-box PocketBook* on the server and to the sync folder on your Device, will be automatically synchronized when the internet connection is on.
- **2.** All synchronized files will be downloaded to the sync folder in the Library (by default, *Dropbox PocketBook* is the sync folder, but you can change it in *Settings > Accounts and Synchronization > Dropbox > Sync folder*).

Manually:

1. To synchronize all content in sync folders, in *Settings* choose 'Accounts and Synchronization > Dropbox > Synchronize files now', or in the Library choose 'Synchronize files now' in the context menu of the sync folder.

After synchronization all obtained files will be also available in the sync folder in the Library on the Device.



Send-to-PocketBook

The application allows to send files to the email address of your Device. Sent books will be automatically downloaded to your Device, if the Wi-Fi is turned on.

How to start using

- Register for the Send-to-PocketBook service, for this purpose do the following:
 - Launch application:
 - from the Applications > Send-to-PocketBook section;
 - or from Settings > Accounts and Synchronization > Send-to-PocketBook.

NOTE: The Wi-Fi connection should be on, otherwise you will be asked to turn it on.

In the opened wizard enter your contact email address and password.

 The email with the activation link will be sent to the specified address. Follow this link to receive the email address of your Device (for example, username@pbsync.com).

NOTE: The contact email address is used only for the authorization of the application, and the service address of the Device <u>username@pbsync.com</u> is used for sending books to it, if you want them to be downloaded to your Device.

2. After activation update the registration wizard on the Device. After that all applications features will be available for you, and the download folder for received books will be created in the library — *Send to PocketBook*.

How to get files

Automatically:

 Files, sent to the service email address of your Device, will be automatically downloaded to the download folder in

the Device Library, when the internet connection is on. Download folder is available after authorization from the locations:

- Applications > Send-to-PocketBook;
- Settings > Accounts and synchronizations > Sendto-PocketBook > Go to folder of the context menu of the Download folder;
 - Library > Send-to-PocketBook.
- **2.** By default, 'Send-to-PocketBook' is the download folder, but you can change it at registration or in the Settings > Accounts and synchronization > Send-to-PocketBook > Download folder section.

Manually:

To update the content of the download folder, in *Settings* choose *Accounts and synchronization > Send-to-Pocket-Book > Receive files now* or in *Library* choose *Receive files now* in the context menu of the download folder.

Received files will be also available in the download folder in the Library of the Device.

The list of trusted senders

Documents can be downloaded on the Device, if they are sent from the address, contained in the 'white list' (a list of the trusted senders).

The address, specified at registration, is contained in the list by default.

If the mail is sent to your Device from the unknown address, you will receive the letter with a proposal to add a sender to the 'white list'. After your confirmation you will receive files from the added address to your Device. Thus, spam won't get on the Device.

In this chapter you will learn how configure the interface and software features of the Device for the most comfortable usage. Select *Settings* at *Notification panel* to configure the Device. All changes will be applied after exiting the section.

If you will encounter any problems with new settings, you will be able to start the Device in safe mode with factory defaults. To start in a safe mode, press and hold **Backward** key during the Device boot.

品WI-FI

In this section you can set parameters needed for network connection.

Network access — **on** or **off**. After network access activation, the following settings appear:

• Connection to hidden networks — read more in the <u>Connecting to the Internet</u> section of this manual.

Available Networks — a list of available networks.
 Choose one of them and you'll see parameters of this connection: Network name (SSID), signal strength, security, IP-address, network mask, main gateway, DNS.

NOTE If Scanning is displayed instead of *Available Networks*, it means that Device is searching for available networks.

ACCOUNTS AND SYNCHRONIZATION

Book Store — in this section you can enter *Login* and *Password* for authorization in the *Book Store*.

PocketBook Sync — There are the following settings for the PocketBook Sync service:

 PocketBook Sync Status: On or off. The service is turned on automatically at the autorization. If you are not

going to use the service for a long period, you can turn off to optimize the Device productivity.

- Downloading via Wi-Fi: On demand (you need to process the list before download) or Automatically (all new files are dowloaded automatically).
- Download folder: location of files. The Downloads folder is set by default. You can choose another folder or create a new one in the internal Device storage or on the external SD-card.
- Login/Exit: if you are not authorized in the application, the page with a list of book stores will appear for choosing and authorization. If you are authorized, then you can logout PocketBook Sync.
- Information about service more detailed about service.

Send-to-PocketBook — the following options are available:

PocketBook account: your account email.

 Login/Log out: if you are not authorized in the application, input your contact email address and password, to authorize. If you are authorized, the email, to which you can send books, is displayed. You can logout Send-to-PocketBook.

- Receive files now: The content of the Download folder will be updated. Before update, please, check if your Device is connected to the Internet
- Receive files automatically: On or Off. Files, sent
 to the Device address <u>username@pbsync.com</u>, will be automatically updated in the download folder, if Wi-Fi connection is on. You can turn off automatic receiving files to
 optimize the Device productivity.
- *Download folder*: location of received files. The *Send-to-PocketBook* folder is set by default. You can choose any other folder or create a new one in the internal Device storage or on the external SD-card.
 - About service more detailed about service.

Dropbox — In this section the following options are available:

- Login/Log out: if you are not authorized in the application, input your Dropbox account data to authorize. If you are authorized, then you can logout Dropbox.
- Synchronize Now: Files in the Sync folder and Pocketbook device directory will be synced. Before syncing files, please check if your Device is connected to the Internet and is linked to the proper Dropbox account
- Autosync: Turn On or Off auto synchronization.
 The service is turned on automatically at the authorization, so Dropbox will automatically sync files, if Wi-Fi connection is on. You can turn off autosync to optimize the Device productivity.
- Sync Folder: location of synced files. You can also move files to Sync folder, if you want to sync them with Dropbox Pocketbook directory on the server. The Dropbox PocketBook folder on the Device is set by default. You can choose another folder or create a new one in the internal Device storage or on the external SD-card.

• About Service — more detailed about service.

ReadRate — In this section the following options are available:

- Remove ReadRate Authorization. After removing all files of events from ReadRate are deleted. Read more about ReadRate in <u>Social networks & ReadRate</u> section.
 - ReadRate Status;
 - ReadRate authorization.

Adobe DRM

To authorize, input your *Login* (e-mail address) and *Pass-word*. When you are authorized, your login and *Remove Adobe DRM Authorization* item are displayed. After removing all protected DRM documents will be unavailable.

PocketBook Cloud — In this section the following options are available:

Login/Log out: if you are not authorized in the application, input your PocketBook Cloud account data to authorize. If you are authorized, then you can logout.

- Synchronize Now: Files in the Download folder and Pocketbook device directory will be synced. Before syncing files, please check if your Device is connected to the Internet and is linked to the proper PocketBook Cloud account.
- Download Folder: location of synced files. You can choose another folder or create a new one in the internal Device storage or on the external SD-card.

About Service — more detailed about service.

F PERSONALIZE

Power-off Logo — the image will be displayed when the Device is off. You can set a cover of the last opened book by setting *book cover*.

NOTE You can also set your own picture as a logo from the *Gallery* application. Read about it in the *Gallery* section.

Fullscreen mode in pdf and djvu formats — you can turn on or turn off the fullscreen mode during reading.

Fullscreen mode in text formats — you can turn on or turn off the fullscreen mode during reading.

Complete Page Refresh. Select the amount of page turned before the screen will be updated completely. Always item provides the best quality, but consumes the most power. Less frequency may cause some artifacts from previous pages on a screen.

Open at Startup last opened book or main menu.

LED Indication - you can turn on or turn of

Status Bar in Reading Mode — you can turn on or turn off the display of status bar during reading.

Complete Page Refresh. Select the amount of page turned before the screen will be updated completely. Always item provides the best quality, but consumes the most power. Less frequency may cause some artifacts from previous pages on a screen.

User Profiles can be configured. Each profile stores individual books' status, last opened books, bookmarks, notes, favorites and pre-configured network connections.

To add new profile, open the corresponding item. You will be suggested to set destination (local memory or SD card) and to enter the name from on-screen keyboard. After this current above-mentioned parameters will be stored at this profile.

To activate profile open the one you need. In profile context menu you can change avatar, rename or delete profile.

LANGUAGES

Language. Select the Device's interface language.

Keyboard Layouts. Under this section you can add up to 3 keyboard layouts.

Available Dictionaries. Under this section you can uncheck dictionaries you don't want to be displayed in the list during the translation or in *Dictionary* application;

Speech synthesis and OCR.



In this section you will be able to set date, time, time zone and clock format. You can also *Synchronize Time* or set *Auto Time Sync* to use the network time/date.

In this section you can configure the folders in which photos and documents captured with the camera will be stored, as well as select the resolution for your images.

() SAVING BATTERY

Here you can see battery level and set parameters, which help to save battery charge:

- · Battery Percentage;
- Auto screen lock set time of idleness, after which the Device is locked: off, 5 min, 10 min.

 Power off after — set time of idleness, after which the Device power off:10, 20, 30, 60 minutes or turn off this setting.



USB Mode — set how the Device handles USB connection by default: *PC link*, *Charge* **or** *Ask when connected.*

Backup & Recovery

- Restore Configuration select the configuration file to restore from a list;
- Backup Configuration to SD this action will create a backup folder on an external microSD-card and will save there system settings. You will be suggested to enter the file name from on-screen keyboard;

Library

This section is intended for optimization of Library database.

• *Library Data Update* – set the parameters for Library database update:

- Off database won't be updated;
- Once database will be updated after exit from Configuration section, the parameter will be set to Off after update;
- Automatically database would be update after each Library opening and copying/removal of books (including microSD card change).
- Optimise Database remove old database entries.
 To run optimization set the parameter to Once and exit Settings. The parameter will be set to Off after optimization.

Privacy

Protect Configurations by Password — in this section you can protect your setting by password. Select Set Password section and type the password from on-screen keyboard. Now each time you try to enter Settings section, you will be asked to enter the password. You can remove or

change password by selecting the corresponding item. To proceed, you will be asked to enter the password once more.

 Diagnostic and Usage — software provides data to PocketBook about some actions, performed by a user on the Device for the further improvement of the Device and services to users. The serial number and any other information for identifying a user isn't saved. You can disable this option of statistics gathering in the Diagnostic and Usage section.

Format Internal Memory – this action will erase all data, except system files.

CAUTION! If you need to erase all data on the Device, use this feature only, don't try to format the Device internal memory via PC.

Format SD card – this action will erase all data from the external microSD card.

Factory Reset – the Device state will be reset to factory default settings, erasing user settings. Other data (e.g. books, photos) won't be lost;

Demo mode - switching demo mode for the Device. To activate demonstration mode check On in the *Demo mode* item.

☑ SOFTWARE

Firmware Version - the current version of firmware is displayed;

Software Update – the Device will search for updates in the following order: microSD card (if installed), internal storage and Internet.

Auto Update – turn on/off automatic check for updates. Thirdd-Party Apps — license and information about third-party applications, used on the Device.

□ ABOUT DEVICE

The following information about Device will be displayed:

Device Model (model, serial number, hardware platform, Wi-Fi MAC address);

Memory (operative memory, total and available internal memory and microSD-card);

License - license and information about applications, used on the Device.

Firmware Update

WARNING! Firmware Update is a responsible operation, during which management software of the Device will be changed. In case of improper execution control program may be damaged and will require treatment in the service centre. Please perform the upgrade procedure in accordance with the instructions below.

There are two ways to update the firmware.

Automatic Update

To start automatic software update select Settings > About Device > Software > Software Update.

The Device will begin to check available update sources in the following order:

- · MicroSD card (if installed);
- Internal memory;
- Internet

If default Internet connection is not set, the Device will ask to connect to one of available wireless networks.

Also you can activate the automatic updates check (Settings > About Device > Software > Auto Update). In this case, the Device will use Wi-Fi connection only.

Manual Update

- **1.** Open site www.pocketbook-int.com. Select your country.
- Click the Support button on top menu. Select hardware model of your Device.
 - **3.** Download the *Firmware* to your PC.
- **4.** Unpack the content of the archive, file SWUPDATE. BIN, and copy it to the root folder of internal Device storage.
 - 5. Switch off the Device by pressing button On/Off.
 - 6. Press and hold both **Backward** and **Forward** buttons.
- **7.** Switch on the Device by pressing **On/Off.** Hold both **Backward** and **Forward** buttons until the message *Firmware update...* is displayed on the screen.

8. Follow the on-screen instructions with pictures: connect USB cable to the Device and Press Menu Key

NOTE: You can check your Firmware version in *Main menu > Settings > About device > Software > Firmware Version*

Troubleshooting

Error Message	Reason	Correction Method
No upgrade image found	File SWUPDATE.BIN cannot be found on the microSD card. Make sure the file is in the root folder of the card.	Delete some files from the Device and copy SWUPDATE.BIN file on it one more time. Repeat the download from www. pocketbook-int.com.
Upgrade image is corrupted or Image is empty	SWUPDATE.BIN file is damaged or there is no space available on the microSD card.	Delete some files from the Device and copy SWUPDATE.BIN file on it one more time. Repeat the download from www. pocketbook-int.com.
File read error	MicroSD card error	Try to use another MicroSD card
Error. A different firmware version is installed on the device	A firmware file of an older version is stored in the device internal memory.	Delete the old version of the firmware file from the Device's internal memory root folder

Troubleshooting

Malfunciton	Possible Reason	Solution
Device does not turn on or turns on but only the logo is loaded	Battery is low	Charge the battery
A book does not open - the message <i>Book is</i> probably damaged or pro- tected appears, or nothing happens at all	The book is damaged	If the book was down- loaded from the online store try to re-load it again. If the file opens on your PC, but does not open on the Device, save the book in another format (TXT, DOC, PDF).
Html book opens but is displayed incorrectly. For example, there are empty pages, some part of the text is missing etc.	HTML-files contain non-text elements (frames, JAVA-scripts, flash-elements)	Save the page in TXT format
Book opens but various symbols, question marks etc. are displayed instead of letters	Incorrect encoding	Switch to reading mode, select <i>Settings</i> and change encoding
No response when you press any key	Sometimes (e.g., when downloading damaged or too large books) the Device may freeze	Close the frozen application by pressing ▲/▼ keys simultaneously for 1–2 sec.

Malfunciton	Possible Reason	Solution
After connection to PC disks are not displayed in Explorer	Your Device is in the bat- tery charging mode.	Check USB mode in Set- tings Main Menu item. Set Connection to PC or Ask at Connection
	No signal in connection cable	Check USB cable condition and its proper connec- tion to connector. Try to connect the USB-cable to another port
Bookmarks, settings and current position in file can- not be saved	File system damaged	Connect the device to a PC and check disks. To pro- ceed, open My Computer, right-click on the selected disk and select Properties > Service > Check Disk
	Internal memory is full	Delete books, images and/ or music files that you do not need
Battery discharges too fast	Disabled automatic turn- ing off	Settings > Date/Time in Main Menu. Select auto- matic turn off time in Auto Turn Off in item

Customer Support

For detailed information about service centers in your country please use contacts below:



Austria	0-800-802-077
Czech Republic	800-701-307
France	0805-080277
Germany	0-800-187-30-03
Israel	1-809-494-246
Italy	800-788-913
Poland	0-0-800-141-0112
Switzerland	0-800-898-720



www.pocketbook-int.com/support/



help@pocketbook-int.com

Compliance with International Standards

Product name: PocketBook Ultra

Model number: PocketBook 650

The EUT should be supplied by USB port from complied Limited Power Source of personal computer or notebook.

The EUT should be supplied by Adapter from complied Limited Power Source.

Rated output voltage: DC 5V 1A.

This equipment is marked with the symbol and can be used throughout the European \mathbf{C} \mathbf{E} community.

This indicates compliance with the R&TTE Directive 1999/5/EC.

France – 2.4GHz for Metropolitan France.

In all Metropolitan departments, wireless LAN frequencies can be used under the following conditions, either for public or private use:

- Indoor use: maximum power (EIRP*) of 100 mW for the entire 2400-2483.5 MHz frequency band;
- Outdoor use: maximum power (EIRP*) of 100 mW for the 2400-2454 MHz band and with maximum power (EIRP*) of 10 mW for the 2454-2483 MHz band

IMPORTANT: Changes or modifications to this product not authorized could void the EMC and wireless compliance and negate your authority to operate the product. This product has demonstrated EMC compliance under conditions that included the use of compliant peripheral devices and shielded cables between system components. It is important that you use compliant peripheral devices and shielded cables between system components to reduce the possibility of causing interference to radios, televisions, and other electronic devices.

Certification information (SAR)

The device meets guidelines for exposure to radio waves.

Your device is a radio transmitter and receiver. It is designed not to exceed the limits for exposure to radio waves recommended by international guidelines. These guidelines were developed by the independent scientific organization ICNIRP and include safety margins designed to assure the protection of all persons, regardless of age and health.

The exposure guidelines for devices employ a unit of measurement known as the Specific Absorption Rate or SAR. The SAR limit stated in the ICNIRP guidelines is 2.0 watts/kilogram (W/kg) averaged over 10 grams of tissue. Tests for SAR are conducted using standard operating positions with the device transmitting at its highest certified power level in all tested frequency bands. The actual SAR level of an operating device can be below the maximum value because the device is designed to use only the power required to reach the network. This equipment complies with the European Council Recommendation of 12 July 1999 on the Limitation of Exposure of the General Public to Electromagnetic Fields [1999/519/EC].

PocketBook International S.A.
Crocicchio Cortogna, 6, 6900, Lugano, Switzerland
Tel. 0800-187-3003

Designed by PocketBook International. Assembled in PRC Contains Reader® Mobile technology by Adobe Systems Incorporated

